



The 15.5 is Coda's flagship Class A stereo amplifier, sharing the design of the 40.0. Optimized for Class A operation, the 15.5 is better suited to low-impedance speaker systems where higher current capability yields superior performance. The optional remote control allows input selection and bias control, and internal controls allow the 15.5 to be bridged into a high-current monoblock.

- | | | |
|---|--|---|
| <ul style="list-style-type: none"> • 150 Watts Class AB into 8 Ohms • 300 Watts Class AB into 4 Ohms • Precision Bias Class A operation to 100 Watts sliding to Class AB at higher output level • Ultra high current non-bridged design • Fully discrete FET differential input stage • Vertical MOSFET Voltage Gain Stage • DC coupled to an ultra wideband bipolar output stage • Very high linear damping with minimal feedback • AC-coupled unbalanced input and true DC coupled balanced input • Double-sided gold plated circuit boards • 3.0kVA toroidal power transformer • Low-impedance power supply filter capacitor array • Graphite anodized aluminum and stainless steel finish • Power supply and Bias status indicators • 10 year warranty / 5 year • Designed, manufactured and assembled in the USA | <p>Rated Power:</p> <p>Frequency Response:</p> <p>Distortion:</p> <p>Gain:</p> <p>Maximum Current:</p> <p>Noise:</p> <p>Input Impedance:</p> <p>Output Impedance:</p> <p>Power Supply:</p> <p>Dimension:</p> <p>Weight :</p> | <p>100W/ch Class A into 8Ω
150W/ch Class AB into 8Ω
300W/ch Class AB into 4Ω
600W bridged Class AB into 8Ω
1200W bridged Class AB into 4Ω</p> <p>DC to 100kHz @ -3dB</p> <p><.02% from 10Hz to 20kHz at rated power</p> <p>26dB</p> <p>>100 Amperes peak per channel</p> <p>-120dB</p> <p>50kΩ unbalanced
10kΩ balanced</p> <p>.03Ω from 20Hz to 20kHz
.06Ω bridged from 20Hz to 20kHz</p> <p>3kVA toroidal power transformer. Dual independent rectification and 200,000uF of power supply filter capacitance</p> <p>17.5" W x 19" D x 7.75" H</p> <p>110 lbs.</p> |
|---|--|---|